

Specifications Ledvance LED Floodlight Endura White 10W 800lm 100D - 830 Warm White | IP44 - Motion and Light Sensor - Symmetrical

[View Product](#)

General Information

| | |
|--------------------------|-------------------------------------|
| SKU | 243563 |
| EAN | 4058075292178 |
| Brand | Ledvance |
| Manufacturer Name | ENDURA FLOOD SENSOR 10W 830 WT LEDV |
| Any Lamp all-in warranty | 5 Years |

Technical Information

| | |
|-----------------------------|-----------------|
| Technology | LED Integrated |
| Wattage | 10 |
| Replaces (Watt) | 10 |
| Voltage (V) | 220-240 |
| Dimmable | Not Dimmable |
| Colour Code | 830 Warm White |
| Colour temperature (Kelvin) | 3000 Warm White |
| Colour Rendering (Ra) | 80-89 |
| Colour of Light | White |
| Light colour options | Single Color |
| Luminous Flux (Lumen) | 800 |
| Luminous Efficacy (lm/W) | 80 |
| Beam Angle (degree) | 120 |

| | |
|-----------------------|----------------|
| Power factor | >0.90 |
| Product Type Category | LED Floodlight |

Fixture Information

| | |
|------------------------|----------------|
| Mounting Method | Surface |
| Including bulb | Yes |
| Fixture Connection | Cable, 3-pole |
| Light Distribution | Symmetrical |
| IP-rating | IP44 |
| Impact Protection (IK) | IK06 - 1 joule |
| Operating Temperature | -10 to +40 |
| Colour of the Fixture | White |
| Housing | Aluminium |
| Colour of material | White |
| Series | Endura |



Dimensions

| | |
|-------------|-----|
| Length (mm) | 168 |
| Width (mm) | 108 |
| Height (mm) | 63 |

Sensor Information

| | |
|----------------|---|
| Type of sensor | Why Any-lamp? Light Sensor, Motion Sensor |
|----------------|---|

| | |
|---------------------------------|-----|
| Sensor Detection Angle (degree) | 120 |
|---------------------------------|-----|

 **Order from the largest lighting specialist in Europe**  **Customised quotation**

| | |
|------------------|---------|
| Sensor Reach (m) | 2 m-9 m |
|------------------|---------|

| | |
|---------------------|-----------------|
| Sensor Time Setting | 10 sec - 10 min |
|---------------------|-----------------|